## How to update firmware TSP143IIILAN/WLAN

- Connect your PC / Laptop with same network with Printer In case of WLAN model you can connect direct to Printer WLAN
- 2. Open Tool MOT2FMEMNIC-300.exe

🌗 MotPackage	27/2/2560 10:46	File folder	
MOT2FMEMNIC_3000.exe	11/9/2557 15:02	Application	29 KB
Readme_TSP100IIILAN_V15.txt	19/12/2559 17:41	Text Document	3 KB
Readme_TSP100IIILAN_V15_JP.txt	19/12/2559 17:42	Text Document	3 KB
ROM_history_for_TSP100IIILAN_V15.doc	19/12/2559 17:44	Microsoft Word 9	61 KB

3. Click "Discovery" for search IP address of printer

Click "Check box" at printer list

Select "File" and Select firmware of Printer "TSP100IIILAN\_Vxx(MAIN)\_Vxx(BOOT).mot" "Uncheck box" Status Protection.

Click "Write" to update firmware

Select Model Name	IP Address	Version	Indicator
TSP143IILAN (ST	R_T-0(192.168.2.84	V1.3	
2			
2			
1			
1	Dis	covery	
1 ):\2)Firmwear Star Printer\#_L	Dise ated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIIL	AN\TSP100IIILAN_V15-b
1 D:\2)Firmwear Star Printer\#_L 7 Model-ID Protection	Disa ated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIIL	AN\TSP100IIILAN_V15-b
1 D:\2)Firmwear Star Printer\#_L 2 Model-ID Protection 3 Status Protection	Disa ated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIIL	AN\TSP100IIILAN_V15-b File
1 D:\2)Firmwear Star Printer\#_L Model-ID Protection Status Protection 4 9100 Multi Session :	Dis ated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIIL	AN\TSP100IIILAN_V15b File

Notice: LED flashing for firmware update

Select	Model Name	IP Address	Version	Indicator	
	TSP143IIILAN (	STR_T-0(192.168.2.84	V1.3		
		Dis	covery		
):\2)Fi	mwear Star Printer∖≠	Dis #_Lated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIII	AN\TSP100IIILAN_V15b	File
D:\2)Fi	mwear Star Printer∖≭ iel-ID Protection	Dis #_Lated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIII	AN\TSP100IIILAN_V15&	File
D:\2)Fi 7 Moo	mwear Star Printer∿≠ del-ID Protection us Protection	Dis #_Lated Firmware_#\1)Thermal\T	covery SP100III\TSP100IIII	AN\TSP100IIILAN_V15-b	File

## Wait until POP-UP Success. Then Click OK

00 . MOT2FMEMNEC Ver3.0.0.0 Select Nodel Name IP Address Version Indicator TSP14300LAN (STR\_T-0(192.168.2.84 V1.5 MOT2FMEMNIC x Success. Please weit for self-reset of the printers. D1/2/Ennwear Star Printer/#\_Lat 15-b File OK [7] Model-ID Protection Satur Protection 9100 Mult Season No change Cancel

Wait until LED Finish Flashing and status LED is ON Please Self-Test for checking firmware version