1. Download Star Quick Setup Utility from App Store or Play Store



- 2. Connect LAN cable to printer
- Check IP Address by Self-Test
 Press and hold "Feed" button and turn printer power on then wait until printer is printing Self -test out then
 release power button



Checking IP Address Device ID : Not registered << Star CloudPRNT >> CloudPRNT Service : DISABLE << Remote Config >> Service : ENABLE ***** ** Current IP Parameters Status **** ************ : 192.168.2.61 IP Address (DHCP) : 255.255.255.0 Subnet Mask Default Gateway : 192.168.2.1

4. Open Star Quick Setup Utility then select printer

Star Quick Setup Utility Ver.1.0.0		〈 Back	Select Printer	S
Selected Printer "C-Pri 192.168.2.61 LAN / Model: mC-Print3 (MCP31L) 00:11:62:1D:28:23	nt3	Searching 🗦	š.	
Top Menu		192.168.2.61		
Start Guide (Initial Settings)	>	LAN / Model: m0 00:11:62:1D:28:	C-Print3 23	
Printer Operation Check	>			
Printer Settings	>			
Online Manual	>			
(i) Others	>			
เลือกปริ้นเตอร์				

5. Choose printer which you want then click "Yes"



6. Click "Printer Setting"



7. Click "Network Setting "

K Back	k Printer Settings			
	Selected Printer 192.168.2.61 LAN / Model: mC-Print3 (MCP31L) 00:11:62:1D:28:23	"C-Print3		
Print S	ettings			
₽ ₪□	Memory Switch Settings	>		
Ŷ	Logo Settings	>		
Interfa	ce Settings			
•*	Bluetooth Settings	>		
€∕	Network Settings	>		
0	Wireless LAN Unit Setting	s >		
	USB Serial Number Settin	gs >		
Cloud	Settings			
	Star CloudPRNT Settings	>		
ද්ධ	Star Micronics Cloud Service Settings	>		
Peripheral Settings				
° (Barcode Reader Settings	>		

Click Detail Setting = Enable
 TCP Port 9100 multi session = Enable
 then click "Apply" for save setting

K Back Network Settings				
DHC	P (Automat	tically	get IP address	
IP Address	. 2.	61		
Subnet Mask 255 . 255	. 255 .	0		
Default Gateway	. 2.	1	1	,
			Detail Setting	gs 💽
DHCP Timeout				
Disconnect Mes	sage		2	\bigcirc
TCP Port 9100 N	Aulti Session			
TCP Port 9100 E	Data Timeout	t (sec)		0 30
SteadyLAN			Disable Enable for	ios
				3

Factory Default



9. Wait until show "Success"

🗸 Back		Net	work	Settings		S
	DHCP	(Autom	naticall	y get IP ad	dress)	
IP Address	3					
192 .	168	. 2	. 6	1		
Subnet Ma	isk					
255 .	255	. 255).[0		
Default Ga	iteway					
192 .	168	. 2		1		
DHCP Tim	eout			Detail S	Settings	
Disconne			Succ	ess		
TCP Port			Oł	¢		
TCP Port 9	9100 Da	ita Timeo	out (sec)		0 30
Stoodyl Al				D	isablo	

10. Self-Test again for check setting > 9100 muti session = Enable

******* Network Configuration ****** MAC Addr(Printer) 00:11:62:1D:28:23 MAC Addr(iPad) 00:11:62:25:E8:23 : 0.0.0.0 IP Address Supnet Mask : 0.0.0.0 Default Gateway : 0.0.0.0 DHCP DHCP Timeout : ENABLE : 8.8.8.8 : 8.8.4.4 DNS 1 DNS 2 "guest" "****** "user" Login Password "root" Login Password Web Refresh Time (Sec.) 9100 Multi Session 9100 Data Timeout (Sec.) Disconnect Message 5 : ENABLE :-0-: DISABLE : DISABLE SteadyLAN << SSL/TLS >> Certificate : Self-Signed Self-Signed Certificate CA-Signed Certificate : Exist : Not exist << Star Micronics Cloud >> Receipt Upload : DISABLE : Not registered Retailer Device Name Device ID : Not registered : Not registered << Star CloudPRNT >>