



How to be setting printer driver Virtual Com Port for SK1-X11 on Windows 10

1. Change emulation of printer to ESC/POS or check emulation of printer by press and hold 'FEED & SELECT' button then plug power cable then printer will be printing configuration setting out. Look at the 'Current Emulation' should be 'ESC/POS'.




1.1 if now is StarPRNT, please change by press 'SELECT' 1 time then press 'FEED' for print all of setting of printer.




2. After printed setting of the printer, press 'FEED' button for change setting.




3. Until found 'ENTER COMMON SETTING?' please press 'FEED' button 1 time.




4. Then press 'FEED' button till found 'USB DEVICE CLASS = PRINTER'.




5. Press 'SELECT' button 1 time for change setting from 'PRINTER' to 'COMMUNICATION'.




6. Press 'FEED' button until found 'ENTER INTERFACE SETTING?' then press 'SELECT' button for finished setting.





7. Connect print to PC/Laptop by Mini USB Cable then will get Com Port.




8. Install printer driver by right click at 'setup.exe' select 'Run as administrator'.




9. Click 'Next' 2 times.





10. Click 'Install'.




11. Will show Utility Driver Installer then click 'Next'.




12. Until finished then click 'Finish' 2 times.




13. Go to Control Panel > Devices and Printers and click 'Add Printer'.




14. Click 'The printer that I want isn't listed'.




15. Select 'Add a local printer or network printer with manual settings' and click 'Next'.




16. Choose Com Port which you get in Devices and Printers then click 'Next'.




17. Click 'Have Disk...'.




18. Click 'Browse' and access 'C:\Program Files (x86)\Sanei Elec Inc\driver\printer_driver_us'.




19. Select the printer which you want and click 'Open' then click 'OK'.




20. Select printer which you want again and click 'Next'.



21. If don't need to setting printer name, please click 'Next'.




22. Can choose Share or Do Not Share then click 'Next'.



The screenshot shows the 'Add Printer' dialog box with the 'Printer Sharing' section. The title bar includes a back arrow, a printer icon, and the text 'Add Printer'. The main heading is 'Printer Sharing'. Below it, a paragraph states: 'If you want to share this printer, you must provide a share name. You can use the suggested name or type a new one. The share name will be visible to other network users.' There are two radio button options: 'Do not share this printer' (which is selected) and 'Share this printer so that others on your network can find and use it'. Below these options are three text input fields labeled 'Share name:', 'Location:', and 'Comment:'. At the bottom right, there are two buttons: 'Next' and 'Cancel'.

23. Click 'Finish'.



The screenshot shows the 'Add Printer' dialog box with the 'Finish' section. The title bar includes a back arrow, a printer icon, and the text 'Add Printer'. The main heading is 'You've successfully added SANEI SK1-31S-UNI-US'. Below it is a checkbox labeled 'Set as the default printer'. A paragraph states: 'To check if your printer is working properly, or to see troubleshooting information for the printer, print a test page.' Below this paragraph is a button labeled 'Print a test page'. At the bottom right, there are two buttons: 'Finish' and 'Cancel'.

24. The printer which you select will be appear in Devices and Printers.

