

*Connect printer by LAN interface and using Lan Cable *Self-Test for Checking the printer get IP Address or not

1. Go to folder 'TSP650II\TSP650II_V70-b20\TS65-268_TSP650II_V70-b20_201903' and open the

pro	ograr	m 'MOT2FMEMNIC	.,		-	_	_	
•	MOT2	MEMNIC Ver2.0.0.0				-		Х
	Select	Model Name	IP Address	Version	Indicator			_
			Disco	verv				
							File	
	Mod	lel-ID Protection						
		us Protection						
	- 0tu							

2. Click 'Discovery' then the IP Address will be show and click 'Select' the IP Address.

MOIZ	MEMNIC Ver2.0.0.0				_		×
Select	Model Name	IP Address	Version	Indicator			
		Dis	scovery				
						File	
Mod 🖂	lel-ID Protection						
≥ stat	us Frotection						
			Write				



3. Click 'File' to find the firmware file

Select	Model Name	IP Address	Version	Indicator	
		Discove	ery		
				File	
Mod	del-ID Protection				
Stat	us Protection				

4. Go to firmware folder and choose the firmware file 'T6II_V70(Main).mot'

TSP650II → TSP650II_V70-b20 → TS65-2	~ <u>5</u>			
older				
^ Name ^	Date modified	Туре	Size	
CH_Model_Font	28/11/2562 11:16	File folder		
JP_Model_Font	28/11/2562 11:16	File folder		
JP2_Model_Font	28/11/2562 11:16	File folder		
TW_Model_Font	28/11/2562 11:16	File folder		
USUK_Model_Font	28/11/2562 11:16	File folder		
T6II_V20(Boot).mot	30/1/2561 7:25	MOT File		20 KB
T6II_V20(Boot)_V70(Main).mot	7/3/2562 7:43	MOT File		1,229 KB
T6II_V70(Main).mot	7/3/2562 7:43	MOT File		1,210 KB

5. Click 'Write'

Discovery	
	File
Model-ID Protection	
Status Protection	
Write	

6. Star updating the firmware by LED flashing, wait till printer will be have sound then self-test for checking the firmware version.

star

7. For update boot version, turn printer power OFF and change DIP SW under the printer > DIPSW2-1=Off and DIPSW2-3 = Off then turn printer power ON

8. Do the same as No.1 but No.4 please choose the boot file 'T6II_V20(Boot).mot'

Name	Date modified	Туре	Size
CH_Model_Font	28/11/2562 11:16	File folder	
JP_Model_Font	28/11/2562 11:16	File folder	
JP2_Model_Font	28/11/2562 11:16	File folder	
TW_Model_Font	28/11/2562 11:16	File folder	
USUK_Model_Font	28/11/2562 11:16	File folder	
T6II_V20(Boot).mot	30/1/2561 7:25	MOT File	20 KB
T6II_V20(Boot)_V70(Main).mot	7/3/2562 7:43	MOT File	1,229 KB
T6II_V70(Main).mot	7/3/2562 7:43	MOT File	1,210 KB

9. Click 'Write' and wait till finished

Discovery	
	File
Model-ID Protection	
Status Protection	
Write	

10. Change DIPSW2-1=ON and DIPSW2-3=ON, and turn printer power Off then self-test for check the boot version again.