How to set TSP100IIIW connect to Router by TSP100III Utility Application **please install TSP100III Utility Application on your phone**

1. Connect printer to smart your device via WiFi Mode (check WiFi name from Self-Test)

Settings		W	Vi-Fi
	Wi-Fi		
~	TSP100III-BB32CA Unsecured Network		? (j)
MY	NETWORKS		
	SMSA-5GHz		e 🗢 🛈

2. Go to TSP100III Utility and click 'Select Device' for select the printer which you connecting

TSP100III Utility Ver.1.6.0				
Bluetooth Setup				
Pairing and Connect Bluetooth	>	< Back	Select Device	Ċ
Selected Device	LAN			
TSP143IIIW (STR_T-001) TCP:192.168.10.1 (00:1d:12:bb:32:ca)	>	TSP143IIIW TCP:192.168.	(STR_T-001) 10.1 (00:1d:12:bb:32:ca)	
Configuration	Bluetooth			

3. Click 'Setting' as below and click 'Device Management' then will move to browser Selected Device



4. Click button on the left top > Login and fill username: root / password: public



- 5. Click button on the left top again > WLAN Setting
- 6. Select 'Access Point Mode'
 - Fill your router name in SSID
 - Change your security router (check from your router properties)
 - Fill your password of your router in Security Key (If no password, no fill)
 - Click 'Submit'



Wireless LAN Settings

Access Point Mode

Infrastructure Mode

SSID TSP100III-BB32CA	
Security NONE	v
Security Key	
Submit	Cancel

7. Check your printer is connecting to your router by Self-Test