

How to set Bluetooth Device Name with Windows (SM-T300i)

*Need to install driver printer before following this instruction.

1. Check Printer mode that on Bluetooth mode or not



1.1. If not press and hold power and feed until screen turn blue



1.2. Press power button until screen show "Bluetooth Mode"





1.3. Then press power and feed at the same time, Printer will print the setting as picture below.



2. Connect Printer with PC by Bluetooth.

Bluetooth & devices > Devices						
*	Bluetooth Discoverable as "SMSA13"	On 🛑				
Pair n	ew device with "SMSA13"	Add device				
Input						
	2.4G Mouse					
Other devices						
۰	Bluetooth LE Device 57699a265b5b Paired					
-	DELL SE2722H					
•	Star Micronics Driver is unavailable					



3. Go to **Devices and Printers** in Control Panel then right click on connected Printer then click Properties. Then click hardware tab and you will see COM port as picture below.

Devices and Printers									
\leftarrow \rightarrow \checkmark \uparrow $\textcircled{$$}$ Control	Panel > All Control P	anel Items > Devices	and Printers						
Add a device Add a printer	Remove device								
~ Devices									
2.4G Mouse Bluetooth LE Device 57699a265b5b	DELL SE2722H	SMSA13							
✓ Printers						1			
DocuCentre-V (2263) Fax	Microsoft Print to PDF	Microsoft XPS Document Writer	OneNote (Desktop)	OneNote for Windows 10	Star Micronics	Create shortcut Create shortcut Create shortcut Create shortcut			
						Properties			
Star Micronics Properties Star Micronics Device Functions: Name Star Micronics Vpe Star Micronics Upe Star Micronics Device Function Summary Device Function Summary									
Manufacturer: Microsoft									
Location: on Bluetooth Device	(RFCOMM Protocol TDI)								
Device status: This device is working	g properly.	ies							
ОК	Cancel	Apply							

4. Open Star Bluetooth Utility for Portable then select COM port same as your Printer COM port. Then press Read.





5. Wait for Reading complete and You can change Bluetooth Device Name in the fill as picture below. After finished press Apply for save Device Name and click OK.

📢 Star Bluetooth Utility for P	ortable	-		×	🙀 Star Bluetooth Utility for P	ortable	_		X
<u>F</u> ile <u>H</u> elp					<u>F</u> ile <u>H</u> elp				
Bluetooth Module Info :	SM-T300IVer3.3				Bluetooth Module Info :	SM-T300IVer3.3			
Device Name :	Star Micronics				Device Name :	Bartender 01			
iOS Port Name :	Edit the iOS Port N Star Micronics	ame			iOS Port Name :	Edit the iOS Port Name Bartender 01			
Auto Connection :					Auto Connection :	ON OFF			
Security Mode :	Disabled (No PIN code	≥)	~		Security Mode :	Disabled (No PIN code)		~	
PIN code :	Change the PIN co	de			PIN code :	Change the PIN code			
		Apply	,				Apply		
Connected: COM4					Connected: COM4				
Star_Bluetooth_Utility				\times					
To apply settings, and establish pair	please turn the devic ring again.	e power Of	FF and O	N,					
			ОК						

- 6. Restart the Printer and Device Name will change.
- 7. For check Bluetooth Device Name you can check it by press and hold Feed and Power button until printer finished print the self-test and check Bluetooth Device Name on receipt as picture below.

